



MACHAKOS UNIVERSITY

University Examination 2018/2019

SCHOOL OF ENGINEERING AND TECHNOLOGY

DEPARTMENT OF ELECTRICAL AND ELECTRONICS ENGINEERING

FIRST YEAR SECOND SEMESTER EXAMINATION FOR

DIPLOMA IN ELECTRICAL AND ELECTRONIC ENGINEERING

EED 115: SOLAR TECHNOLOGY SYSTEMS

DATE: 29/4/2019

TIME: 2.00-4.00 PM

INSTRUCTIONS:

Answer question and any other two questions

QUESTION ONE (30 MARKS)

- a) State any three advantages of renewable energy (3 marks)
- b) Explain the problem caused by,
 - i. oversizing a battery
 - ii. undersizing a battery. (4 marks)
- c) Calculate the approximate power conversion efficiency of a poly-crystalline PV module at an ambient temperature if the solar irradiance is 950W/m^2 , I_{mp} is 5.00A, V_{mp} is 17.8V and the size of the module 0.68m^2 (4 marks)
- d) With the aid of a well labeled diagram, explain the following solar PV systems:
 - i. stand alone
 - ii. Hybrid system. (4 marks)

e) After a comprehensive site survey, the following details were collected;

Load description	Quantity	Wattage (W)	Total Wattage	Daily use in hours	Weekly use Days/week	Average Daily load
LED lights (Bed room)	2	6		3	6	
LED lights (Bath room)	1	6		1	5	
LED lights (living room)	3	6		5	6	
LED lights (kitchen)	1	6		2	6	
Radio (AC)	1	30		5	5	
Television (AC)	1	60		5	4	
Laptop charger (AC)	2	40		3	4	
Mobile phone charger (AC)	4	2		3	5	

- i. Determine the total watt-hours for each category. (2 marks)
- ii. Determine the average daily load for each load . (2 marks)
- iii. Determine the total daily DC energy (1 mark)
- iv. Determine the total daily AC energy (1 mark)
- v. Determine the total daily energy requirement (1 mark)

Given that,

days of autonomy = 5

Depth of discharge = 75%

Derating factor = 0.8

Peak sun hours (PSH) = 4.5 hours

Safety factor = 1.25

DC losses = 5%

Inverter efficiency = 90%

Buffer for growth = 10%

Battery equalization factor = 1.1

System voltage = 12 V

Design a suitable system to serve the customer adequately (8 marks)

QUESTION TWO (20 MARKS)

- a) Explain the term photovoltaic effect. (2 marks)
- b) Given that the irradiance in Nyeri is 900w/m^2 and 4 sunshine hours per day are experienced. How much insolation is given by the sun
- Per day
 - Per week (4 marks)
 - Explain the technical specifications found on a genuine PV module. (10 marks)
- c) Explain the term voltage equalization and how it is done. (4 marks)

QUESTION THREE (20 MARKS)

- a) State any five activities involved in final inspection and commissioning of a solar PV project. (5 marks)
- b) Figure 1 is given below,



Figure 1

- b) For each case, calculate the total voltage and total power. (5 marks)
- c) The following details are given,
 $P_{mp} = 20\text{W}$, $V_{mp} = 18\text{V}$, $I_{mp} = 1.11\text{A}$, $V_{oc} = 21.6\text{V}$, $I_{sc} = 1.28\text{A}$, Irradiance = 1000w/m^2 and area A of the PV module = 0.68m^2 .
Calculate the (i) Efficiency of the PV module and (ii) the fill factor. (5 marks)
- d) With the aid of a well labeled I-V curve explain the effect of temperature on the output voltage (5 marks)

QUESTION FIVE (20 MARKS)

- a) Define the following terms with reference to solar PV design.
- i. Peak sun hours
 - ii. cycle
 - iii. Days of autonomy
 - iv. Depth of discharge
 - v. Airmass
- (10 marks)
- b) Explain how sulfation and stratification are prevented. (4 marks)
- c) With the well labeled waveforms, explain any three types of stand alone inverters (6 marks)

QUESTION FIVE (20 MARKS)

- a) Explain any four components of a solar PV systems. (8 marks)
- b) State any four voltage levels managed by the charge controller (4 marks)
- c) Explain why dissimilar PV modules should not be connected in series. (2 marks)
- d) Details of solar pv project are as follows.

Load	Quantiy	Rated watts	Daily use (hours)	Weekly use (days)
LED lights	3	6	3	6
Incandescent lamps	2	20	4	5
Radio (AC)	1	30	5	4

Determine the daily energy requirements and the battery size (6 marks)